Yu-wen Qian, Meng Tian, Xue Jiang, Hua-ju Song, Feng Shu, Jun Li, 2015. Performance analysis for a two-way relaying power line network with analog network coding. *Frontiers of Information Technology & Electronic Engineering*, **16**(10):892-898. [doi:10.1631/FITEE.1500135]

Performance analysis for a two-way relaying power line network with analog network coding

Key words: Power line communication, Outage probability, Symbol error rate, Signal attenuation

Contact: Yu-wen Qian E-mail: admon1999@163.com ORCID: http://orcid.org/0000-0001-9503-549X

Introduction

- Severe signal fading and impulsive impose many unsolved challenges on reliable communications over long-distance power lines.
- To resolve the problem, we study a two-way relaying PLC system, where two sources exchange information with the help of an intermediate relay implementing analogue network coding.
- We derive the outage probability, symbol error rate, and average capacity performance of the relaying PLC system.

The system mode of an in-home PLC network



Performance analysis

- Outage: $P(\gamma \leq \gamma_{\rm th}) \cong 1/2 + \Psi_{\gamma_{\rm eq}}(\gamma_{\rm th})$
- $P_{\text{SER}} \approx \frac{m}{2\pi} \frac{1}{2\sqrt{\pi}} \sum_{j=1}^{l} H_j \left(\frac{1}{2} + \sum_{i=1}^{l} H_i\right)$ • Average capacity: $\int_{-1}^{1} \sqrt{2} \int_{i=1}^{l-1} H_{i}$ $\int_{-1}^{1} \frac{\ln q_{i}^{2}}{\ln e^{2\sigma\sqrt{2}s_{t}+2\mu}+nc} - 2\mu}{\ln e^{2\sigma\sqrt{2}s_{t}+2\mu}-aq_{i}^{2}} \int_{-1}^{2} \frac{\ln q_{i}^{2}}{2\sqrt{2}\sigma} \int_{-1}^{1} \frac{\ln q_{i}^{2}}$

$$\overline{C} = \sum_{i=1}^{l} \sum_{j=1}^{l} H_i H_j \log_2 \left(1 + \frac{p_S}{\sigma^2} \frac{e^{2\mu + 2\sigma v_j} e^{2\sqrt{2}\sigma s_i + 2\mu}}{be^{2\sqrt{2}\sigma s_i + 2\mu} + c + ae^{2\mu + 2\sigma v_j}} \right) \frac{e^{2\sqrt{2}\sigma s_i + 2\mu} \left(1 - \frac{ae^{2\mu + 2\sigma v_j}}{be^{2\sqrt{2}\sigma s_i + 2\mu} + c + ae^{2\mu + 2\sigma v_j}} \right)}{be^{2\sqrt{2}\sigma s_i + 2\mu} + c} \cdot \frac{2a\sigma e^{2\mu + 2\sigma v_j} \left(be^{2\sqrt{2}\sigma s_i + 2\mu} + c + ae^{2\mu + 2\sigma v_j} \right) - 2\sigma e^{2\mu + 2\sigma v_j}}{(bs_i + c + ae^{2\mu + 2\sigma v_j})^2}.$$

Simulation results



Fig. 2 Average outage probability against average received SNR with $\sigma=3$ dB and $\sigma=10$ dB



Fig. 3 Symbol error rate against average received SNR with $\sigma=3$ dB and $\sigma=10$ dB



Fig. 4 Average system capacity against SNR with $\sigma=3$ dB and $\sigma=10$ dB

Conclusions

- In this paper, the performance of the relaying PLC system based on analog networking is presented.
- The formula of the PDF of received SNR is derived.
- We have also found that introducing a two-way relay can significantly improve the performance of a PLC system.